Ignoring unity multipliers, the cascade uses six coefficient multiplications and six additions per sample; the generic expanded FIR has six nonunity coefficients and six additions. Both use six delays. There is no generic arithmetic reduction, although coefficient storage in the identical-section cascade can be two shared parameters and numerical scaling can be arranged per stage.