Comparative cost and preferred method

Generic direct-form II uses three feedback and three nonunity feedforward multiplications, six additions, and three delays. The first/second-order cascade has the same generic counts. Two allocated full biquads would waste one state and may waste zero multiplications; removing those yields the canonical realization. No universal floating-point superiority is inferred from algebraic equivalence.